

## FEATURES

1-800-234-6831 . Wide, smooth response · Uniform cardioid pattern

· Rupped die-cast construction

Electro - Voice, Inc. 600 Cer. 1 St. Buchanan, MI 49107 616-695-6831

metallic disphragm permits smooth response over a wide frequency range and withstands high humidity. temperature extremes, severe mechanical shocks.

## and the correstve effects of salt sir. It is practically indestructible with normal usc.

The Klentro-Voice model 601 is a cardioid microphono of the dynamic type with only one moving element. It is designed specifically for public address applications. The cardioid pattern is obtained through use of three sound entrances located in the back of the disphragm. These three sound entrances. each utilizing the proper acoustical impedance, combine to form one effective back entrance which varies In distance" from the diaphragm inversely with frequency. The resulting phase and amplitude conditions produce a uniform cardioid pattern over a wide frequency cange. This variable front-to-back distance along with dynamic-type construction offords high resistance to mechanical shock and eliminates proximity effect.

DESCRIPTION AND APPLICATIONS

The Model 864 is an all-ourpose public address migrophone designed to fulfill requirements of widerange reproduction under a great variety of conditions. Because of its excellent and uniform polar response, it is especially useful in locations where acoustic feedback, ambient noise, and severe reverberation exist. The preferred instrument for serious home and semi-professional recording, the 664 is also an ideal choice for quality sound reinforcement systems, particularly where accustic problems exist. It is equipped with a pop-proof wire mesh grille which minimizes wind and breathblasts. The Model 664 may be used on a floor- or deskstand or carried in the hand.

This all-purpose microphone features the exclusive Electro-Voice Acoustallov® disphragm. The non-

\* Variable-D. H. S. Patent No. 3, 113, 207

## SPECIFICATIONS Generating Element Francency Response:

Uniform from 60 to 15,000 Hz

CARDIOID MICROPHONE

Impedance: 150-ohm and high lespedance. 150ohm impedance is balanced to ground. Microphone is wired for high impedance unless 150 ohm is requested.

Impedance Selection: Selection is made at cable plug. To change from high to 150ohm impedance, move white lead at

terminal #2 to terminal #8. Output Level: 150-ohm. -58 dbt. FIA sensitivity ralfny. -149 db High Impedance, -58 db\*\*. ElA

sensitivity rating, -151 db + 0 db = 1 mw/10 dvnc/cm2 \*\* 0 db = 1 volt/dvne/cm2

Polar Pattern: Cardioid, uniform front-to-back discrimination. See Figure 2.

Diaphragm: Electro-Voice Acoustalloy® Case Pressure-cast zinc Finish Satin Chrome (available in nonreflecting gray as model 664A or in

decurative gold as model 664G. Dimensions: Diameter: 1-7/8 inch. maximum Leagth: 7-3/16 inch. not including stud. See Figure 3

Net Weight: 1 lb., 12 oz., without cable

Cable: 15 ft. two-conductor, shielded, synthetic rubber jacketed, broadcast type, equipped with model QC-481 Electro-Voice Quick-Change Connector.

Stand Coupler: 5/8 in. -27 thread on stud.
Optional Accessories: Model 419 drak stand
Warranty: Electro-Voice Model 554 microphone
is guaranteed against defects in workmanship and materials.




Figure 1 .- Response Curve

## ARCHITECTS' AND ENGINEERS'

The microphone shall be a cardioid, dynamic type, with uniform frequency response from 60 to 15,000 Hz. The disphragm shall be non-metallic Acoustalloy and shall have a magnetic shield to prevent dust and iron particles from reaching the diaphragm. Available impedance shall be 150-ohm and high-impedance. It shall be possible to obtain the impedance desired by moving one connection in the microphone connector. Line shall be balanced to ground on low-impedance and phased. The microphone shall be provided with three sound entrances located in the microphone case at different distances in back of the disphrasm. These three entrances, each utilizing the proper scoustical impedance, shall combine to form one effective back entrance which varies in distance from the disphragm inversely with frequency. The resulting phase and amplitude conditions shall provide a uniform cardfold pattern at all frequencies.

The output level for 150-chm impedance shall be-58 db with 0 db equalling 1 mw/10dynes/cm<sup>2</sup>. Output level for high-tropodance shall be-58 db with 0 db equalling 1 volt/dyne/cm<sup>2</sup>. EIA sensitivity rating shall be -149 db for 150-ohm impedance and -151 db for high-impedance.

The case shall be usual of pressure-cast also. The microphose shall be a maximum disorder; of 1. 7/8 in., he length of 7-4/5 in., not including stud. of 7-8 in., not including stud. and a new weight of 1 lb., 12 on., less cable. Pittish shall be satis chrome (if model 664A. Pittish shall be not-reflecting rays of if model 666A, final bett of the convergence of the converg

The microphone shall include a stand coupler with a 5/8 in. -27 thread on stud. The Electro-Voice Model 884 (or 884A or 884G) is specified.



Figure 2 - Polar Pattern



Figure 3 - Dimensions




Figure 4 - Wiring Diegram




Figure 5 - Wiring Diagram, Modified

INSTRUCTIONS FOR MODIFYING MODEL 664 FOR USE WITH RELAY CONTROL 1. Remove nameplate and switch from stud.

- Discomment and tape the green transformer lead from switch Lug #4 (center). Green lead from Pin #4 of cable connector remains connected to switch Lug #4.
- Connect jumper from switch Lug #1 to switch Lug #5.
- Disconnect and tape rod leads from switch Lug #6.
- If microphone is to be used for occasional VOX operation in addition to relay operation, remove yellow leads from switch Lug #3, solder logether and insulate with tape.
- Wiring for relay operation is now complete. Replace switch and nameplate.

The cable may now be connected to obtain relay country labelines plan I and a of the indexphone connector. The write cable lead is indexplored connector. The write cable lead is indexplored control, and the black cable lead earlier posterior. The cable shield for ground returns for businessing the control of the cable shield for ground returns for the circuits. Use of AC for relay control is not recommended. Hum and noise may be picked up by the high tumpedance lead.

IMPEDANCE CHANGE PROCEDURE FOR E-V QUICK-CHANGE CONNECTOR
For added convenience and flexibility, an Electro-

You about convenience and lexibility, an Electro-Voice imnovation, the QC-4M Quick-Change Connector, is now supplied with your Model 664. Change from-high impedance (Hi-Z) to low-impedance (Lo-Z), or the reverse, can now be made quickly and easily without tools.

Figure A shows the basic internal wiring diagram of E-V dual impedance unicrophones.




Figure A - Wiring Diagram

Note that moving white cable conductor from Pin #2 to Pin #3 converts the microphone from Hi-Z to Lo-Z.

- To change impadance, proceed as follows:
- Remove agble from microphone by turning the connector shell to left (counter clockwise) until free and then gently pull it away from the microphone.
- Gripping connector; shell firmly in one hand and cable (near connector) in other hand, firmly push cable into shell so that moided plastic insert slipe from shell. (See figure B)
- 3. Separate molded insert as shown in figure C.




Figure B Figure C Figure D

 Note that cable shield and conductors are connected "slip in" pins. Shield pin is in hole #1 of alignment frame, and pin on black conductor is in hole 44. These should not be changed.

 The pin connected to the white conductor of the cable should be inserted in hole #2, if high impedance operation is desired, or hole #3 if low impedance is desired. (See figure D)

Snap moided insert balves into position. (See figures B and C)
 Firmly push connector shell back into position

(reverse of Step 2). Pressure will be required, since these parts are designed to provide close fit. 8. Align connector guide pin with key slot in the

microphone and allip connector into position.

Tighten connector shell by turning in clockwise

direction.

Your E-V dual impedance microphona is now ready for operation in the impedance you have selected.